

## Acer Projector Quick Reference Guide

Acer projector specifications and comparison chart

	New	New	New	New
Model	PD112	PD321	PD520	PD720
Display	DLP™	DLP™	DLP™	DLP™
Resolution	Native SVGA (800 x 600), SXGA (1,280 x 1,024) compressed	Native XGA (1,024 x 768), SXGA (1,280 x 1,024) compressed	Native XGA (1,024 x 768), SXGA (1,280 x 1,024) compressed	Native XGA (1,024 x 768), SXGA (1,280 x 1,024) compressed
Contrast Ratio	2000:1	2000:1	1800:1	2000:1
Brightness (typical)	1,300 ANSI Lumens	1,100 ANSI Lumens	1,500 ANSI lumens	2,300 ANSI Lumens
Lamp Life	2,000 Hours	2,000 Hours	2,000 Hours	2,000 Hours
Audio	No Support	No Support	One Internal Speakers with 2 watts Output	2 Internal Speakers Each with 3 watts Output
Weight	4.5 lbs (2Kg)	2 lbs (.99Kg)	3.5 lbs (1.7Kg)	6.6 lbs (3Kg)
Dimension	272 x 211 x 86 mm (10.7" x 8.3" x 3.4")	198 x 148 x 57 mm (7.8" x 5.8" x 2.2")	246 x 210 x 71 mm (9.68" x 8.27" x 2.8")	277 x 225 x 85 mm (10.9" x 8.9" x 3.3")
Remote Mouse Control	Wireless remote with optional mouse control	Credit card-sized wireless remote	Remote mouse control with laser pointer	Remote Control with Mouse Function & Laser Pointer
<b>I/O Connectors :</b>				
<b>Computer Input</b>	1 HDB 15-Pin D-Sub (VGA/Component/HDTV input port)	1 HDB 15-Pin D-Sub (VGA/Component/HDTV input port)	• 35-pin VESA M1 (RGB / digital / component / HDTV) • 1 HDB 15-Pin D-Sub (through M1 connector)	• 1 HDB 15-Pin D-Sub (VGA/Component/HDTV input port) • 1 DVI Connector
<b>AV Input</b>	• 1 Mini DIN for S-Video Input Connector • 1 RCA Jack for Composite Video Input Connector	• 1 Mini DIN for S-Video Input Connector • 1 RCA Jack for Composite Video Input Connector	• 1 Audio Mini Jack • 1 Mini DIN for S-Video Input Connector • 1 RCA Jack for Composite Video Input Connector • 1 Audio Mini Jack (S-Video / Composite Video)	• 2 Audio Mini Jack (1 for 15-pin D-SUB, 1 for DVI) • 1 Mini DIN for S-Video Input Connector • 1 RCA Jack for Composite Video Input Connector • 1 Audio Mini Jack (S-Video / Composite Video)
<b>Output</b>	• 1 USB for optional remote Mouse • 1 Mini D-SUB 15-Pin for Monitor Loop Through	• 1 USB for optional remote Mouse	• 1 Remote Mouse Port	• 1 Mini D-SUB 15-Pin for Monitor Loop Through • 1 Audio Mini Jack for monitor loop through • 1 Remote Mouse Port
<b>Standard Accessories</b>	AC Power Cord 15-Pin VGA Signal Cable (1.8 M) RCA Composite/HDTV Video Cable 15-Pin VGA to component/HDTV adapter S-Video Signal Cable Wireless Remote Control AA Type Batteries x 2 for remote multi-language user's guide (CD-ROM) multi-language quick start guide lens cap (hanging) soft carrying bag	AC Power Cord 15-Pin VGA Signal Cable (1.8 M) RCA Composite/HDTV Video Cable S-Video Signal Cable Credit card-type remote Control Battery for remote multi-language user's guide (CD-ROM) multi-language quick start guide lens cap (hanging) soft carrying bag	AC power cord VESA M1-A to VGA and USB cable mini DIN 4-pin S-Video cable 3.5mm phone jack to RCA pin composite video cable mini phone jack to mini phone jack audio cable wireless remote control with USB mouse function and two batteries multi-language user's guide (CD-ROM) multi-language quick start card lens cap soft carrying bag	AC Power Cord 15-Pin VGA Signal Cable (1.8 M) RCA Composite/HDTV Video Cable Audio cable jack/RCA S-Video Signal Cable Wireless Remote Control with mouse function and laser AA Type Batteries x 2 for remote multi-language user's guide (CD-ROM) multi-language quick start card lens cap soft carrying bag
<b>Part Number</b>	EY.J0201.001	EY.32101.001	EY.52001.001	EY.72101.001

These products are available in South Africa at ComX. Please visit <http://www.LaptopDirect.co.za> for more.